

## DIAMOND



# RF VSWR Meter: SX1100 Quad-Band

The SX1100 measures forward and reflected power and VSWR. Compact size makes meter useful for testing both base and mobile installations. Two directional couplers with switch and LED indicators for in-line connection of two transceivers.

### Special Features:

- Illuminated meter
- Switchable r.m.s. or peak power
- Measures forward, reflected & VSWR power
- 6"W x 2"H x 4"D, 2 lbs.

### Specifications:

Frequency MHz: 1.8-160, 430-450, 800-930, 1240-1300

Power range : 5/20/200 W

Minimum Power SWR Test: 4W

Connectors: HF-VHF: SO-239, UHF: Type-N

DIMOND ANTENNA CORPORATION

Miyata building No.15 chome, sugamo, Toshimaku Tokyo Japan-1700002

Tel:03-3947-114, Fax : 03-3944-2981, <http://dimond-ant.co.jp> , Email: [oversease@dimond-ant.co.jp](mailto:oversease@dimond-ant.co.jp)